



Mehrstrahl-Sicherheits-Lichtschranken MSL

MSLZ02-20331, PSZ01-1401





Sender/Empfänger in einem Gehäuse

Typ > [MSLZ02-20331](#)
 Artikelnr. > [1016264](#)

Spiegel

Typ > [PSZ01-1401](#)
 Artikelnr. > [1015897](#)

- Aktiv überwachte Halbleiterausgänge
- Integrierte Funktionen
- Nur eine aktive Seite, dadurch weniger Verdrahtungsaufwand
- Modulares Sicherheitsmuting mit MSM

Hinweis: Das Produkt wurde abgekündigt. Die Nachfolge ist applikationsabhängig. Ein mögliches Nachfolgeprodukt finden Sie in der [M4000 Produktfamilie](#).

Nähere Informationen erhalten Sie von Ihrer SICK-Vertretung.



Funktionen-Sender/Empfänger in einem Gehäuse

Systemaufbau:	Aktiv/Passiv-System
Wiederanlaufsperr:	✓
Schützkontrolle:	✓
Strahlkodierung:	✓
Muting:	-
Muting mit Override:	-
Sichere Gerätekommunikation über EFI/SDL:	-

Technische Daten-System

Maximale Systemreichweite: 4,5 m

Technische Daten-Sender/Empfänger in einem Gehäuse

Strahlanzahl:	2
Reichweite von ... bis:	0 ... 7,5 m
Abmessungen Breite x Tiefe x Höhe:	52 x 55 x 1.285 mm

Gewicht:	4,19 kg
Typ:	Typ 4 (IEC 61496)
Ansprechzeit:	15 ms
Versorgungsspannung typisch, von, bis:	DC, 24 V, 19,2 V, 28,8 V
Leistungsaufnahme:	< 12 W
Schaltspannung von ... bis:	U _v - 3V, U _v
Maximaler Schaltstrom:	500 mA
Wellenlänge:	880 nm
Schutzklasse:	1
Schutzart:	IP 65
Anschlussart:	steckbarer Klemmenanschlussraum
Betriebsumgebungstemperatur von ... bis:	0 ... 55 °C
Schwingfestigkeit (geprüft nach):	5 g (IEC 68-2-6)
Schwingfrequenz von ... bis:	10 ... 55 Hz
Schockfestigkeit:	10 g, nach IEC 68-2-29
Leitungslänge:	70 m

Technische Daten-Spiegel

Strahlabstand:	400 mm
Abmessungen Breite x Tiefe x Höhe:	52 x 55 x 668 mm

Australia

Phone +61 3 9457 0600
1800 334 802 – tollfree
E-Mail sales@sick.com.au

Belgium/Luxembourg

Phone +32 (0)2 466 55 66
E-Mail info@sick.be

Brasil

Phone +55 11 3215-4900
E-Mail sac@sick.com.br

Canada

Phone +1 905 771 14 44
E-Mail information@sick.com

Ceská Republika

Phone +420 2 57 91 18 50
E-Mail sick@sick.cz

China

Phone +86 4000 121 000
E-Mail info.china@sick.net.cn
Phone +852-2153 6300
E-Mail ghk@sick.com.hk

Danmark

Phone +45 45 82 64 00
E-Mail sick@sick.dk

Deutschland

Phone +49 211 5301-301
E-Mail kundenservice@sick.de

España

Phone +34 93 480 31 00
E-Mail info@sick.es

France

Phone +33 1 64 62 35 00
E-Mail info@sick.fr

Great Britain

Phone +44 (0)1727 831121
E-Mail info@sick.co.uk

India

Phone +91-22-4033 8333
E-Mail info@sick-india.com

Israel

Phone +972-4-6801000
E-Mail info@sick-sensors.com

Italia

Phone +39 02 27 43 41
E-Mail info@sick.it

Japan

Phone +81 (0)3 3358 1341
E-Mail support@sick.jp

Magyarország

Phone +36 1 371 2680
E-Mail office@sick.hu

Nederlands

Phone +31 (0)30 229 25 44
E-Mail info@sick.nl

Norge

Phone +47 67 81 50 00
E-Mail austefjord@sick.no

Österreich

Phone +43 (0)22 36 62 28 8-0
E-Mail office@sick.at

Polska

Phone +48 22 837 40 50
E-Mail info@sick.pl

România

Phone +40 356 171 120
E-Mail office@sick.ro

Russia

Phone +7-495-775-05-30
E-Mail info@sick.ru

Schweiz

Phone +41 41 619 29 39
E-Mail contact@sick.ch

Singapore

Phone +65 6744 3732
E-Mail admin@sicksgp.com.sg

Slovenija

Phone +386 (0)1-47 69 990
E-Mail office@sick.si

South Africa

Phone +27 11 472 3733
E-Mail info@sickautomation.co.za

South Korea

Phone +82 2 786 6321/4
E-Mail info@sickkorea.net

Suomi

Phone +358-9-25 15 800
E-Mail sick@sick.fi

Sverige

Phone +46 10 110 10 00
E-Mail info@sick.se

Taiwan

Phone +886-2-2375-6288
E-Mail sales@sick.com.tw

Türkiye

Phone +90 (216) 528 50 00
E-Mail info@sick.com.tr

United Arab Emirates

Phone +971 (0) 4 8865 878
E-Mail info@sick.ae

USA/México

Phone +1(952) 941-6780
1 800-325-7425 – tollfree
E-Mail info@sickusa.com

More representatives and agencies
at www.sick.com